TITLE OF THE INVENTION

IMAGE SENSING APPARATUS AND METHOD, PROGRAM, AND

STORAGE MEDIUM

5 FIELD OF THE INVENTION

The present invention relates to an image sensing apparatus having a lookup table arithmetic processing section, and a method, a program, and a storage medium therefor.

10

BACKGROUND OF THE INVENTION

In recent years, to improve color reproduction of an image sensed by an image sensing apparatus such as a digital camera, more complex image processing is used to convert

15 image data, which is obtained by A/D-converting an image from a CCD, into a final output image. Examples of the image processing are color conversion processing corresponding to chromatic adaptation as a human color perception characteristic and color conversion processing for

20 converting a color into a memory color that is felt by humans as desirable.

The present applicant has developed a processing method using a three-dimensional lookup table for the above image processing. However, in the color conversion

25 processing corresponding to chromatic adaptation, to change color reproduction in accordance with a change in photographing light source (color temperature),

three-dimensional lookup table data equal in number to
light sources corresponding to photographing light sources
(color temperatures) must be held, as shown in, e.g., Fig. 4
of Japanese Patent Laid-Open No. 8-9241. However, the

5 size of the three-dimensional lookup table data is very
large. To hold a plurality of three-dimensional lookup
table data, the memory capacity in the image sensing
apparatus must be increased. To hold three-dimensional
lookup table data equal in number to light sources is not

10 realistic from the viewpoint of cost. There is another
method in which three-dimensional lookup table data equal
in number to a minimum number of light source color
temperatures are held, and at the time of photographing,
interpolation arithmetic processing corresponding to the

15 light source color temperature at that time is executed
using the three-dimensional lookup table to create
three-dimensional lookup table data corresponding to the
light source color temperature. However, the less the
number of three-dimensional lookup tables becomes, the

20 lower the color conversion accuracy becomes. In addition,
since at least two three-dimensional lookup tables are
still necessary, the memory capacity must also be
increased.

25   SUMMARY OF THE INVENTION
     The present invention has therefore been made in
consideration of the above-described problems, and has as

its object to decrease the memory capacity required for a lookup table.

In order to solve the above-described problems and achieve the object, according to the first aspect of the present invention, there is provided an image sensing apparatus which causes an image processing section to execute image processing to convert digital image data, which is obtained by A/D-converting an output from an image sensing element, into output image data, wherein the image processing section comprises a matrix arithmetic processing section and an N-dimensional (N is a positive integer) lookup table arithmetic processing section and causes the matrix arithmetic processing section to process the digital image data before the N-dimensional lookup table arithmetic processing section.

According to the second aspect of the present invention, there is provided an image sensing apparatus which has an image sensing element and an A/D conversion section which A/D-converts an output from the image sensing element, causes an image processing section to execute image processing to convert digital image data obtained from the A/D conversion section into output image data, and records the output image data in a recording medium, wherein the image processing section comprises a white balance processing section, a matrix arithmetic processing section, and an N-dimensional lookup table arithmetic processing section where N is an integer not less than 3

and causes the matrix arithmetic processing section to process the digital image data before the N-dimensional lookup table arithmetic processing section.

According to the third aspect of the present invention, there is provided an image sensing method which comprises an image processing step of sensing an image of an object with an image sensing element and an A/D conversion processing step of A/D-converting an output from the image sensing step, and executes image processing in an image processing step to convert digital image data obtained in the A/D conversion processing step into output image data, wherein the image processing step comprises a matrix arithmetic processing step and an N-dimensional (N is a positive integer) lookup table arithmetic processing step and processes the digital image data in the matrix arithmetic processing step before the N-dimensional lookup table arithmetic processing step.

According to the fourth aspect of the present invention, there is provided a program causing a computer to execute the above image sensing method.

According to the fifth aspect of the present invention, there is provided a computer-readable storage medium storing the above program.

Other features and advantages of the present invention will be apparent from the following description taken in conjunction with the accompanying drawings, in which like reference characters designate the same or

similar parts throughout the figures thereof.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a block diagram showing the schematic arrangement of an image sensing apparatus according to an embodiment of the present invention;

Fig. 2 is a block diagram showing the arrangement of an image processing section;

Fig. 3 is a diagram showing a digital signal after A/D conversion; and

Fig. 4 is a diagram showing a digital image signal after interpolation processing.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

A preferred embodiment of the present invention will be described below in detail with reference to the accompanying drawings.

Fig. 1 is a block diagram showing the schematic arrangement of an image sensing apparatus according to an embodiment of the present invention.

An image sensing section 101 including a lens system, stop, and shutter forms the image of an object on an image sensing surface of a CCD 102. The object image formed on the CCD 102 is photoelectrically converted into an analog signal. The analog signal is sent to an A/D conversion section 103 and converted into a digital image signal. The digital image signal generated by the A/D conversion

section 103 is sent to an image processing section 104 and converted into an output image signal. The output image signal undergoes format conversion in a format conversion section 105 to obtain a JPEG format or the like. Then, the image signal is written in the internal memory of the image sensing apparatus or an external memory such as a compact flash memory (registered trademark) by an image recording section 106. The flow of data in the image sensing apparatus has been briefly described above.

The image processing section 104 will be described in more detail.

Fig. 2 is a block diagram showing processing sections included in the image processing section 104 in Fig. 1. The flow of image processing in the image sensing apparatus according to this embodiment will be described below with reference to the block diagram shown in Fig. 2.

The digital image signal output from the A/D conversion section 103 shown in Fig. 1 is sent to a white balance processing section 201 shown in Fig. 2. The color temperature of the light source is detected from the digital image signal, and a white balance coefficient that represents white in the image as a write signal is obtained. The gain of the digital image signal is adjusted using the obtained white balance coefficient. The digital image signal that has undergone the white balance processing is sent to an edge enhancement processing section 207 and interpolation processing section 202. In the

- 6 -

interpolation processing section 202, interpolation

arithmetic processing is performed using pixels at

positions R, G1, G2, and B in the pixel layout of a single-CCD

as shown in Fig. 3, thereby creating surface data for R,

5   G1, G2, and B as shown in Fig. 4.

As is known, chromatic adaptation as a human color

perception characteristic changes depending on the color

temperature. For example, under evening glow or an

incandescent lamp, the human eye cannot completely adapt

10   and recognizes a white object as not write but a color with

an orange tone. To cope with such chromatic adaptation of

the human eye (to cope with a change in color reproduction

due to a change in light source color temperature), a matrix

arithmetic processing section 203 determines a matrix

15   coefficient to be used for matrix arithmetic processing on

the basis of the light source color temperature obtained

by the white balance processing section 201 and executes

a matrix arithmetic operation. The matrix arithmetic

processing is executed for each pixel using:

$$
\begin{vmatrix} Rm \\ Gm \\ Bm \end{vmatrix} = \begin{vmatrix} M11 & M21 & M31 & M41 \\ M12 & M22 & M32 & M42 \\ M13 & M23 & M33 & M43 \end{vmatrix} \begin{vmatrix} R \\ G1 \\ G2 \\ B \end{vmatrix}
$$

20   ...Equation (1)

How to obtain the matrix coefficient will briefly be

described below.

Matrix coefficients corresponding to color

temperatures, i.e., a matrix coefficient MTX3K for a light

25   source color temperature of 3,000 K or less, a matrix

- 7 -

coefficient MTX4K for 4,000 K, a matrix coefficient MTX5K for 5,000 K, a matrix coefficient MTX6K for 6,000 K, and a matrix coefficient MTX7K for 7,000 K or more are prepared in advance in the matrix arithmetic processing section.

5   Here, a matrix coefficient MTX for a light source color temperature of 5,300 K should be obtained. First, the matrix coefficients of the upper and lower light source color temperature levels are selected. In this case, the matrix coefficient MTX5K for 5,000 K and the matrix

10   coefficient MTX6K for 6,000 K are selected. The matrix coefficient corresponding to the light source is obtained using the selected matrix coefficients in accordance with:

$$\text{MTX} = (5300 - 5000)/1000 \times \text{MTX5K} +$$

$$(6000 - 5300)/1000 \times \text{MTX6K} \quad \text{...Equation (2)}$$

15   However, when the color temperature of the light source is 3,000 K or less,

$$\text{MTX} = \text{MTX3K} \qquad\qquad\qquad \text{...Equation (3)}$$

When the color temperature of the light source is 7,000 K or more,

20   $$\text{MTX} = \text{MTX7K} \qquad\qquad\qquad \text{...Equation (4)}$$

The digital image signal that has undergone the matrix arithmetic processing is sent to a gamma processing section 204. The gamma processing section 204 converts the data using:

25   $$Rg = \text{GammaTable}[Rm] \qquad \text{...Equation (5)}$$

$$Gg = \text{GammaTable}[Gm] \qquad \text{...Equation (6)}$$

$$Bg = \text{GammaTable}[Bm] \qquad \text{...Equation (7)}$$

where GammaTable represents a one-dimensional lookup table.

The digital image signal that has undergone the gamma processing is sent to a three-dimensional lookup table arithmetic processing section 205.

The three-dimensional lookup table arithmetic processing will be described below. The three-dimensional lookup table arithmetic processing according to this embodiment converts three-dimensional data of R, G, and B from R, G, and B signals that have undergone the matrix processing into R, G, and B signals that take memory color reproduction into consideration. More specifically, R, G, and B signals are converted into colors that are memorized by humans as desirable colors. For example, a blue sky is converted from blue into blue green, grass is converted from yellowish green into green, and a skin is converted into a more pinkish flesh color. In this embodiment, to decrease the capacity of the three-dimensional lookup table, the minimum to maximum values of the R, G, and B signals are divided into nine parts to prepare $9 \times 9 \times 9 = 729$ three-dimensional representative lattice points. R, G, and B signals other than the representative lattice points are obtained by interpolation. Interpolation is performed on the basis of the equations given below. Since the image data undergoes the matrix arithmetic in advance in accordance with the color temperature, it is unnecessary to prepare a three-dimensional lookup table corresponding

to each color temperature.

Let R, G, and B be the input R, G, and B signals,
Rout(R,G,B), Gout(R,G,B), and Bout(R,G,B) be output R, G,
and B signals, Ri, Gi, and Bi be the signals at
representative lattice points having values which are
smaller than and closest to the signal values,
Rout(Ri,Gi,Bi), Gout(Ri,Gi,Bi), and Bout(Ri,Gi,Bi) be the
representative lattice point output signals, and Step be
the step width of the representative lattice points. Then,
we have

$$R = Ri + Rf$$
$$G = Gi + Gf$$
$$B = Bi + Bf$$

Rout(R,G,B) = Rout(Ri+Rf,Gi+Gf,Bi+Bf) =
(Rout(Ri,Gi,Bi) $\times$ (Step - Rf) $\times$ (Step - Gf) $\times$
(Step - Bf)
+ Rout(Ri+Step,Gi,Bi) $\times$ (Rf) $\times$ (Step - Gf) $\times$
(Step - Bf)
+ Rout(Ri,Gi+Step,Bi) $\times$ (Step - Rf) $\times$ (Gf) $\times$
(Step - Bf)
+ Rout(Ri,Gi,Bi+Step) $\times$ (Step - Rf) $\times$ (Step -
Gf) $\times$ (Bf)
+ Rout(Ri+Step,Gi+Step,Bi) $\times$ (Rf) $\times$ (Gf) $\times$ (Step
- Bf)
+ Rout(Ri+Step,Gi,Bi+Step) $\times$ (Rf) $\times$ (Step - Gf)
$\times$ (Bf)
+ Rout(Ri,Gi+Step,Bi+Step) $\times$ (Step - Rf) $\times$ (Gf)

$$\times (Bf)$$

$$+ \; Rout(Ri+Step,Gi+Step,Bi+Step) \times (Rf) \times (Gf) \times (Bf))/(Step \times Step \times Step) \qquad \ldots Equation\ (8)$$

$$Gout(R,G,B) = Gout(Ri+Rf,Gi+Gf,Bi+Bf) =$$

$$(Gout(Ri,Gi,Bi) \times (Step - Rf) \times (Step - Gf) \times (Step - Bf)$$

$$+ \; Gout(Ri+Step,Gi,Bi) \times (Rf) \times (Step - Gf) \times (Step - Bf)$$

$$+ \; Gout(Ri,Gi+Step,Bi) \times (Step - Rf) \times (Gf) \times (Step - Bf)$$

$$+ \; Gout(Ri,Gi,Bi+Step) \times (Step - Rf) \times (Step - Gf) \times (Bf)$$

$$+ \; Gout(Ri+Step,Gi+Step,Bi) \times (Rf) \times (Gf) \times (Step - Bf)$$

$$+ \; Gout(Ri+Step,Gi,Bi+Step) \times (Rf) \times (Step - Gf) \times (Bf)$$

$$+ \; Gout(Ri,Gi+Step,Bi+Step) \times (Step - Rf) \times (Gf) \times (Bf)$$

$$+ \; Gout(Ri+Step,Gi+Step,Bi+Step) \times (Rf) \times (Gf) \times (Bf))/(Step \times Step \times Step) \qquad \ldots Equation\ (9)$$

$$Bout(R,G,B) = Bout(Ri+Rf,Gi+Gf,Bi+Bf) =$$

$$(Bout(Ri,Gi,Bi) \times (Step - Rf) \times (Step - Gf) \times (Step - Bf)$$

$$+ \; Bout(Ri+Step,Gi,Bi) \times (Rf) \times (Step - Gf) \times (Step - Bf)$$

$$+ \; Bout(Ri,Gi+Step,Bi) \times (Step - Rf) \times (Gf) \times (Step - Bf)$$

$$+ \; Bout(Ri,Gi,Bi+Step) \times (Step - Rf) \times (Step - Gf) \times (Bf)$$

$$+ \; Bout(Ri+Step,Gi+Step,Bi) \times (Rf) \times (Gf) \times (Step - Bf)$$

$$+ \; Bout(Ri+Step,Gi,Bi+Step) \times (Rf) \times (Step - Gf) \times (Bf)$$

$$+ \; Bout(Ri,Gi+Step,Bi+Step) \times (Step - Rf) \times (Gf) \times (Bf)$$

$$+ \; Bout(Ri+Step,Gi+Step,Bi+Step) \times (Rf) \times (Gf) \times (Bf))/(Step \times Step \times Step) \qquad ...Equation \; (10)$$

Here, the input signals Rf, Gf, and Bf correspond to gamma-processed digital image signals Rg, Gg, and Bg, and the output signals Rout, Bout, and Gout correspond to Rt, Bt, and Gt, respectively.

Using the above arithmetic processing, the input R, G, and B signals (Rg, Gg, and Bg) are converted into output R, G, and B signals (Rt, Gt, and Bt).

The digital image signal that has undergone the three-dimensional lookup table arithmetic processing is sent to an edge synthesis processing section 206.

In the edge enhancement processing section 207, edges are detected from the digital image signal which is white-balance-processed and sent from the white balance processing section 201, and only an edge signal is extracted. The extracted edge signal is amplified by gain amplification and sent to the edge synthesis processing section 206. The edge synthesis processing section 206

adds the edge signal to the Rt, Gt, and Bt signals sent from the three-dimensional lookup table arithmetic processing section 205.

In this embodiment, the sets of matrix coefficients are prepared in advance in the matrix arithmetic processing section every 1,000 K from 3,000 K to 7,000 K. However, the color temperatures and the number of matrix coefficients prepared in advance are not limited to these. The number of sets of matrix coefficients may be increased to more accurately cope with a change in color reproduction due to a change in light source color temperature. Even when the number of sets of matrix coefficients is increased, it does not always increase the memory capacity because the data amount of one set of matrix coefficients is small, as compared to the case wherein the number of lookup tables is increased by one.

The table in the three-dimensional lookup table arithmetic processing section 205 uses 9 X 9 X 9 lattice points. However, the present invention is not limited to this. The number of lattice points may be changed in accordance with the memory capacity of the image sensing apparatus and the required color conversion accuracy. Interpolation arithmetic processing from near lattice points is not limited to equations (8), (9), and (10). Any other interpolation arithmetic processing such as tetrahedral interpolation may be used.

In this embodiment, gamma processing is executed

before three-dimensional lookup table arithmetic processing. However, the order of processing operations is not limited to this, and either processing can be executed first on the basis of the relationship between the

5   arithmetic accuracy and the buffer memory of the image sensing apparatus. For example, to decrease the buffer memory capacity, gamma processing is executed first to decrease the number of bits of the digital image signal and then, the three-dimensional lookup table arithmetic

10   processing is executed. In this case, the number of bits of the lattice point data of the three-dimensional lookup table can also be decreased. Hence, the capacity of the three-dimensional lookup table data can be decreased. Conversely, when the three-dimensional lookup table

15   arithmetic processing is executed before the number of bits is decreased, the conversion arithmetic processing can be executed without decreasing the arithmetic accuracy.

As described above, according to the above embodiment, digital image data (R, G, and B signals)

20   obtained by A/D-converting image data from the CCD 102 is processed by the matrix arithmetic processing section 203 before the processing by the three-dimensional lookup table arithmetic processing section 205. For this reason, it is unnecessary to prepare a three-dimensional lookup table for

25   each color temperature. The memory color conversion can be executed using only one three-dimensional lookup table.

In the above embodiment, a three-dimensional lookup

table is used. However, the present invention can be applied not only to a three-dimensional lookup table but also an arbitrary N-dimensional (N is a positive integer) lookup table such as a one-dimensional lookup table

5   prepared for each of the R, G, and B colors, a two-dimensional lookup table, or a four-dimensional lookup table for C, M, Y, and G.

[Other Embodiment]

The present invention may be applied to a system

10   constituted by a plurality of devices (e.g., a host computer, an interface device, a reader, a printer, and the like) or an apparatus comprising a single device (e.g., a copying machine, a facsimile apparatus, or the like).

The object of the present invention is achieved even

15   by supplying a storage medium (or recording medium) which stores the program codes of software that implements the functions of the above-described embodiment to the system or apparatus and causing the computer (or CPU or MPU) of the system or apparatus to read out and execute the program

20   codes stored in the storage medium. In this case, the program codes read out from the storage medium implement the functions of the above-described embodiment by themselves, and the storage medium which stores the program codes constitutes the present invention. The functions of

25   the above-described embodiment are implemented not only when the readout program codes are executed by the computer but also when the operating system (OS) running on the

computer performs part or all of actual processing on the
basis of the instructions of the program codes.

The functions of the above-described embodiment are
also implemented when the program codes read out from the
storage medium are written in the memory of a function
expansion card inserted into the computer or a function
expansion unit connected to the computer, and the CPU of
the function expansion card or function expansion unit
performs part or all of actual processing on the basis of
the instructions of the program codes.

As described above, according to the above
embodiments, the memory capacity required for the lookup
table can be decreased.

As many apparently widely different embodiments of
the present invention can be made without departing from
the spirit and scope thereof, it is to be understood that
the invention is not limited to the specific embodiments
thereof except as defined in the appended claims.